



013859B

013859A

Standard all models - 25 ft. cord - 1.0 HP

611 Models	Volts	Phase	Mode	Amps
*E611	230	1	Nonauto	6.9
J611	200	3	Nonauto	4.3
F611	230	3	Nonauto	3.7
G611	460	3	Nonauto	1.9
BA611	575	3	Nonauto	1.6

Standard all models - 25 ft. cord - 3.0 HP

641 Models	Volts	Phase	Mode	Amps
*E641	230	1	Nonauto	17.0
J641	200	3	Nonauto	11.0
F641	230	3	Nonauto	9.6
G641	460	3	Nonauto	4.8
BA641	575	3	Nonauto	3.9

Standard all models - 25 ft. cord - 1.5 HP

621 Models	Volts	Phase	Mode	Amps
*E621	230	1	Nonauto	8.9
J621	200	3	Nonauto	5.9
F621	230	3	Nonauto	5.1
G621	460	3	Nonauto	2.6
BA621	575	3	Nonauto	2.0

Standard all models - 25 ft. cord - 5.0 HP

651 Models	Volts	Phase	Mode	Amps
*E651	230	1	Nonauto	28.0
J651	200	3	Nonauto	17.5
F651	230	3	Nonauto	15.2
G651	460	3	Nonauto	7.6
BA651	575	3	Nonauto	6.1

Standard all models - 25 ft. cord - 2.0 HP

631 Models	Volts	Phase	Mode	Amps
*E631	230	1	Nonauto	12.0
J631	200	3	Nonauto	7.8
F631	230	3	Nonauto	6.8
G631	460	3	Nonauto	3.4
BA631	575	3	Nonauto	2.7

Standard all models - 25 ft. cord - 7.5 HP

661 Models	Volts	Phase	Mode	Amps
J661	200	3	Nonauto	25.3
F661	230	3	Nonauto	22.0
G661	460	3	Nonauto	11.0
BA661	575	3	Nonauto	9.0

*All single phase units require external starting capacity and relay circuits.

For information on additional Zoeller products refer to catalog on Variable Control Switches, FM0526; Piggyback Variable Level Float Switches, FM0477; Electrical Alternator, FM0486; Mechanical Alternator, FM0495; Sump/Sewage Basins, FM0487; Alarm System, FM0732; Simplex Controls, FM1596; Rail Systems, FM0787; and Junction Boxes FM1597.

CAUTION

All installation of controls, protection devices and wiring should be done by a qualified licensed electrician. All electrical and safety codes should be followed including the most recent National Electrical Code (NEC) and the Occupational Safety and Health Act (OSHA).

RESERVE POWERED DESIGN

For unusual conditions a reserve safety factor is engineered into the design of every Zoeller pump.