

ITT

BCMC

Residential Water Systems

CentriPro

Magnetic Contactor 1Ø Control Boxes

For 3-wire, 1½ – 5 HP Submersible Motors



1½ – 3 HP

5 HP is in larger enclosure

FEATURES

- Built-in Magnetic Contactors allow the use of standard pressure switches, prolong switch life and eliminate the need to source and install separate contactors, saving installation time and reducing total system component costs.
- Voltage Relay for installer convenience
- 230 volt standard models – 208 volt relay, 9K479 available for low voltage applications
- Start Capacitors for starting torque
- Run Capacitors for efficiency and quiet operation
- Type 3R enclosure for indoor or outdoor mounting
- Accepts up to #2 AWG wire
- Multiple knockouts and two ground terminals
- Manual reset overloads on 1½ – 5 HP models



CentriPro is a brand of ITT Corporation.


www.centripro.com

Engineered for life

AGENCY LISTINGS



TESTED TO UL AND CSA STANDARDS BY UL.



ITT

Residential Water Systems

MAGNETIC CONTACTOR (MC) CONTROL BOXES FOR 3 WIRE, 1Ø, 4" CENTRIPRO MOTORS AND 4" (6", 5 HP) FRANKLIN ELECTRIC MOTORS

Control Box Order Number	HP	KW	Volts	Replaces GP #	Replaces RJ #	Replaces FE #	Standard Circuit Breaker	Standard Fuse	Dual Element Time Delay Fuse	Enclosure Dimensions W x D x H (in)	Shipping Wt. (lbs)
CB15412MC	1.5	1.1	230	No Equal	No Equal	No Equal	30	35	20	8.1 x 5.9 x 9.3	8
CB20412MC	2	1.5	230	00084MC	No Equal	2823018310	25	30	20		
CB30412MC	3	2.2	230	00094MC	S300N1CBC	2823028310	40	45	30		
CB50412MC	5	3.7	230	00104MC	S500N1CBC	2821139310	60	80	45	11 x 6.7 x 12.5	15

"K" REPAIR PARTS FOR MAGNETIC CONTACTOR "MC" CONTROL BOXES

Control Box Order Number	HP	KW	Volts	Capacitor Repair Part Number	Capacitor Type	Capacitor Mfd.	Capacitor Voltage	Capacitor Quantity	Contactor Order Number	Overload Order Number	Start Relay Order Number ①
CB15412MC	1.5	1.1	230	9K447	Start	105-126	250	1	9K485	9K493	9K458
				9K452	Run	10	370			9K480 (S)	
CB20412MC	2	1.5		9K447	Start	105-126	250			9K472 (M)	
				9K451	Run	20	370			9K473 (S)	
CB30412MC	3	2.2		9K453	Start	208-250	250			9K474 (M)	
				9K454	Run	45	370			9K475 (S)	
CB50412MC	5	3.7	9K455	Start	270-324	330	1	9K486	9K475 (S)	9K459	
			9K456	Run	40	370	2		9K476 (M)		

Repair parts above are compatible with and replace parts in old Goulds Pumps or Franklin Electric control boxes.

① If supply voltage is between 200 V – 210 V a 208 V start relay, order no. 9K479, is required.



CentriPro is a registered trademark of ITT Corporation. ITT, the Engineered Blocks Symbol and Engineered for Life are Registered trademarks of ITT Manufacturing Enterprises, Inc.

SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE.

BCMC January, 2010

Copyright (c) 2010 ITT Corporation

Engineered for life